



PM-2501

STEREO PRE-AMPLIFIER 2 ZONES

With the PM-2501, you now have a 10-channel preamplifier whose signals can be transmitted to two zones. Each channel has its own individual volume control and is ideal for connecting up a microphone or other sources. You have a choice between XLR connections (9), MIC/LINE (5), RCA (4) and REC OUT (1).



It is quite a complex process to regulate control in this central concourse. The PM-2501 provides the manageable solution!

zones	2
direct output	yes (REC)
LED level indicator	yes - per zone
tone control	yes - per zone
output	2 x XLR
amp in	-
pre-amp out	-
MIC input	2 - 6 XLR
	7 - 10 XLR / RCA
AUX input	-
tape input	-
chime function	yes (2/4-tone)
priority levels	MIC 2 / 4 VOX
protection	-
cooling	-
power supply	AC 230V / 50Hz - DC 24V
power consumption	13W
dimensions (h x w x d)	484 x 295 x 44mm
weight	3.9kg
extra	-
accessories	MIC-511C / MIC-621A

