


SMART IN SET



SMART IN SET comes with 1 active and 1 passive speaker.



range	<50 m ²
system	2-way coaxial
woofer	6" neodymium
tweeter	1" neodymium titanium dome
power	60W
sensitivity	87dB
impedance	4Ω
frequence range	55Hz - 20kHz
network	Wifi: IEEE802.11 b/g/n 2.4G, Ethernet: RJ45
Bluetooth	5.0
audio input	Bluetooth, Line in
audio output	speaker 4-8 Ω
streaming protocol	Spotify Connect, AirPlay 2, Tidal Connect, DLNA, UPnP, Qplay
online music	Internet Radio, Spotify, Tidal, Qobuz, Napster, Amazon Music,
	iHeartRadio, vTuner, SoundMachine, RadioParadise,
	Calm Radio, QQ Music, QQ FM
local music	mobile device, NAS storage
multizone function	AirPlay 2, Alexa
control	4STREAM app (iOS + Android)
power supply	24V / 4.16A
dim. cut-out (Ø)	210mm
dim. (Ø x d)	235 x 108 mm (passive speaker : 235 x 100 mm)
weight / piece	1,5kg (passive speaker 1,2kg)

